

JEPRO TIME SWITCH INSTRUCTION MANUAL

- ❖ First press the '**UP**' key until it shows reset on display, after that release the '**UP**' key.
- ❖ After '**reset**' is gone from the screen, press '**set**' key. You will see '**t**' on the screen.
- ❖ Then press '**enter**' key, and set the clock minute with the help of '**up**' and '**down**' key.
- ❖ Later set the clock hour with the help of '**up**' and '**down**' key. (Set the clock time according to 24 hour).
- ❖ In the next step press '**enter**' key and there is '**t0 ON**' on the screen, press enter then.
- ❖ With '**up**' and '**down**' key set the minute as per your '**ON**' time, press enter after.
- ❖ With '**up**' and '**down**' key set the hour as per your '**ON**' time, press enter after.
- ❖ There is '**t0 OFF**' on the screen, press enter and then set the minute of off time.
- ❖ Press enter and then set the hour of off time.
- ❖ Press enter key then there is screen shows '**t1 ON**' then the second '**ON**' time set according to '**t0 ON**' and set it as per new '**ON**' time
- ❖ Press enter key then there is screen shows '**t1 OFF**' then the second '**OFF**' time set according to '**t0 OFF**' and set it as per new '**OFF**' time
- ❖ You can set the “**ON-OFF**” times 14 times as above.
- ❖ At the end after pressing '**set**' key your program with 14 “**ON-OFF**” time will be set.

SPECIALITY OF JEPRO TIME SWITCH

- ❖ Arrange “**ON-OFF**” time set as per requirement according to above instruction than press **SET KEY** number of times to save than remaining diverts to bypass.
- ❖ **i.e.** if we have limit of 14 times to ring the bell and we have to ring the bell 7 times than remaining 7 times will diverts to the bypass.
- ❖ Press **ENTER KEY** for manually “**ON-OFF**”, than 4 digits will blink than do it **UP KEY** for ‘**ON**’ and **DOWN KEY** for ‘**OFF**’. Again press **ENTER** for **AUTO MODE**.
- ❖ For set every new “**ON-OFF**” time, Press **UP KEY** until it show **RESET** than set “**ON-OFF**” time according to upside.